


# Rimage® Amigo™ II Specifications

This document provides product specification information for the Rimage Amigo II autoloader. For more information on how to operate and identify the parts of the Amigo II, refer to the *Rimage® Amigo II User Guide*.

 **Note:** For printer specifications, refer to the Rimage Everest or Prism printer specifications document available on the [Rimage Support site](#). **Navigate:** Printer Family > Everest or Prism printer > Specifications tab.

		Amigo II	
<b>Standard system</b>	One disc recorder, Rimage Amigo II autoloader, Everest printer or Prism <i>Plus</i> printer, and software		
<b>Input bin capacity</b>	300 Discs		
<b>Output bin capacity</b>	300 Discs		
<b>Physical size</b>			
<b>Width</b>	15.75 in (40.0 cm)		
<b>Height</b>	22.5 in (57.15 cm)		
<b>Depth</b>	24.5 in (62.23 cm)		
<b>Weight</b>	57 lb (25.85 kg)		
<b>Weight with Everest</b>	102 lb (46.27 kg)		
<b>Weight with Prism</b>	77 lb (34.93 kg)		
<b>PC requirements</b>	 <b>Important!</b> If you do not understand these requirements, ask your computer technician for help or refer to your PC documentation.		
	<b>Minimum Requirements</b>	<b>Optimum Requirements*</b>	
<b>Processor</b>	Celeron, 2.0 GHz	Pentium 4, 2.8 GHz, 400 MHz Front Side Bus	
<b>RAM/Memory</b>	512MB, DDR-200	512MB, DDR-400	
<b>Fixed storage</b>	2 GB of free space	Two 36 GB, 10,000 RPM Serial ATA Hard drives: <ul style="list-style-type: none"> <li>• Drive one is used to house the operating system and the Rimage System Folder</li> <li>• Drive two is used for caching. Format drive as Basic Disk, NTFS</li> </ul>	
<b>Graphics</b>	1024 x 768, 16-bit color	1024X768, 32-bit High Color	
<b>FireWire/USB</b>	2.0 Card included with system	2.0 Card included with system	
<b>Supported operating systems</b>	<ul style="list-style-type: none"> <li>• Windows 2000 SP4</li> <li>• Windows XP SP1 or SP2</li> <li>• Windows 2003</li> </ul>	<ul style="list-style-type: none"> <li>• Windows 2000 SP4</li> <li>• Windows XP SP1 or SP2</li> <li>• Windows 2003</li> </ul>	
<small>*These PC specifications are recommended if you are using the Rimage Amigo II to record DVDs. Throughput is based on this system configuration. For optimum performance, use a PC with these specifications.</small>			

Amigo II	
<b>Software requirements</b>	Rimage Producer Software Suite
<b>Networking ability</b>	To submit orders from a networked PC, refer to the <i>Rimage Advanced Setup Guide</i> .
<b>Power</b>	100 – 240 VAC, 4.7 – 2.3 Amps, 60/50 Hz
<b>Media requirements</b>	Refer to your <i>Everest Printer User Guide</i> or <i>PrismPlus! Printer User Guide</i> for the correct media requirements.
<b>Ribbon requirements</b>	Refer to your <i>Everest Printer User Guide</i> or <i>PrismPlus! Printer User Guide</i> for the correct printer ribbons.
<b>Label design requirements</b>	Refer to your <i>Everest Printer User Guide</i> or <i>PrismPlus! Printer User Guide</i> for the correct label design requirements.
<b>Temperature and humidity</b>	
<b>Operating temperature</b>	60° to 95° F (16° to 35° C)
<b>Humidity</b>	40% to 80% non-condensing
<b>Storage temperature</b>	5° to 95° F (-15° to 35° C)