


# Rimage® DL5200™ and DLN5200™ Specifications

This document provides product specification information for the Rimage DL5200 and DLN5200 autoloaders. For more information on how to operate and identify the parts of these products, refer to the *Rimage® DL5200/DLN5200 User Guide*.

 **Note:** For printer specifications, refer to the Everest printer specifications document available on the [Rimage Support site](#). **Navigate:** Printer Family > Everest II, III, or 600 > Specifications tab.

	DL5200	DLN5200
<b>Standard system</b>	Rimage DL5200 autoloader, an Everest printer, and Rimage software.	Rimage DLN5200 autoloader, an Everest printer, a network-ready embedded PC, and Rimage software.
<b>Number of recorders</b>	2	2
<b>Physical size</b>		
<b>Height</b>	23.25 in (59.1 cm)	23.25 in (59.1 cm)
<b>Width*</b>	14.5 in (36.8 cm)	14.5 in (36.8 cm)
<b>Depth**</b>	23.5 in (59.7 cm)	23.5 in (59.7 cm)
<b>Weight</b>	47.0 lb (21.3 kg)	53 lb (24.0 kg)
<b>Weight with Everest</b>	92.0 lb (41.7 kg)	98 lb (44.5 kg)
	* Allow an additional 2.4 in (6.1 cm) of space for the door to swing open. ** Leave an additional 3.5 in (9 cm) for cabling.	
<b>Minimum PC requirements</b>	Pentium 4 2.8 GHz, 512MB L2 Cache, 800MHz FSB 512MB DDR2-200, 400Mhz Bus One open PCI slot for the provided FireWire®/USB card <b>Rimage recommends 4 hard drives:</b> <ul style="list-style-type: none"> <li>• One drive for the OS</li> <li>• One drive for the Rimage System Folder</li> <li>• Two drives for caching (one for each recorder)</li> </ul> <b>Supported operating systems:</b> <ul style="list-style-type: none"> <li>• Microsoft Windows® 2000 Professional SP 4</li> <li>• Microsoft Windows XP Professional SP2</li> <li>• Windows Server 2003</li> </ul>	Celeron D 340 processor with 533Mhz Front Side Bus 512MB DDR2-400, SDRAM Windows XP Embedded with Service Pack 2 Two 36 GB, Serial ATA, 10,000 RPM, 8 MB cache, Hard Drives <b>Supported operating system:</b> The DLN5200 has an embedded operating system. The DLN5200 and software will function only with the embedded operating system.

	<b>DL5200</b>	<b>DLN5200</b>						
<b>Software requirements</b>	Operates <b>only</b> with the Producer Software Suite.	Ships with the correct software installed on the embedded PC. Operate <b>only</b> with the Rimage software installed on the embedded PC.						
<b>Input bin capacity</b>	One removable 50-disc bin							
<b>Output capacity</b>	Five single-disc output trays and one 75-disc output bin							
<b>Networking ability</b>	Refer to the Rimage Advanced Setup Guide for instructions on submitting orders from a networked computer.							
<b>Power</b>	100 – 240VAC, 60/50 Hz, 4.7 – 3.7 Amps							
<b>Media requirements</b>	Refer to your printer user guide for the correct media requirements. Rimage Media Kits™ are designed for optimum recording and print performance.							
<b>Ribbon requirements</b>	Refer to your printer user guide for the correct printer ribbons. Rimage Media Kits™ include the required print ribbons.							
<b>Label design requirements</b>	Refer to your printer user guide for label design requirements.							
<b>Temperature and humidity</b>	<table border="0"> <tr> <td style="padding-right: 20px;"><b>Operating temperature</b></td> <td>60° to 80° F (15.5° to 26.7° C)</td> </tr> <tr> <td><b>Humidity</b></td> <td>40% to 80% non-condensing</td> </tr> <tr> <td><b>Storage temperature</b></td> <td>5° to 95° F (-15° to 35° C)</td> </tr> </table>		<b>Operating temperature</b>	60° to 80° F (15.5° to 26.7° C)	<b>Humidity</b>	40% to 80% non-condensing	<b>Storage temperature</b>	5° to 95° F (-15° to 35° C)
<b>Operating temperature</b>	60° to 80° F (15.5° to 26.7° C)							
<b>Humidity</b>	40% to 80% non-condensing							
<b>Storage temperature</b>	5° to 95° F (-15° to 35° C)							